



### CP-3500 & CP-3600(+) Load Specifications

#### Panel Operation on AC Voltage

	<u>120VAC</u>	<u>240VAC</u>
Standby	138mA	36mA
Alarm (All NAC Outputs and Alarm Relays)	149mA	55mA

#### Panel Operation on DC Voltage (Battery Backup)

Standby	100mA
Standby (After 15 Minutes)	89mA
Alarm w/1 NAC Active	210mA
Alarm w/2 NAC Active	250mA
Alarm w/Relay "A" & 1 NAC Active	210mA
Alarm w/Relay "A" & 2 NAC Active	260mA
Alarm w/All Relays Active (Including NAC)	280mA
Alarm w/All Relays Active (NOT Including NAC)	160mA

PLEASE NOTE: If NACs are not used there is no external load on the panel or repeaters. The numbers presented above are for control panel and repeater and repeater/relay combination loads only. Use separate load calculation sheets for NACs loads.